

Letters to the Editor

The Board of Editors does not hold itself responsible for opinions expressed in the letters published in this section. The notes containing short reports of original investigations communicated to this section should not contain many figures and should not exceed 500 words in length. The contributions reaching the Secretary by the 15th of any month may be expected to appear in the issue for the next month. No proof will be sent to the author.

1

ON THE NON-COHERENT FORMATION OF ABSORPTION LINES IN STELLAR ATMOSPHERES

SANTI RANJAN DAS GUPTA

DEPARTMENT OF MATHEMATICS, UNIVERSITY OF NORTH BENGAL, RAJA RAMMOHUNPUR

(Received January 13, 1964)

The equation of transfer for partly coherent and partly non-coherent formation of absorption lines in stellar atmospheres can be written as

$$\mu \frac{dI_\nu(t, \mu)}{dt} = (1 + \eta_\nu)I_\nu(t, \mu) + (1 - \epsilon) \cdot a \cdot \eta_\nu J_\nu(t) + (1 + \epsilon \eta_\nu)B_\nu(t) + (1 - \epsilon)b \cdot \eta_\nu J(t), \dots \quad (1)$$

where $I_\nu(t, \mu)$ is the specific intensity of radiation of frequency ν in the direction $\theta = \cos^{-1}\mu$ and at the optical depth t measured in the continuous absorption coefficient k_ν , k_ν being constant over the width of the line considered. $t = 0$ corresponds to the outer surface of the atmosphere supposed to be stratified in plane parallel layers. $J_\nu(t)$ is the average intensity.

ϵ = fraction of atoms excited by radiation of frequency ν and prevented from contributing to the coherent re-emission by superelastic collisions.
 ϵ is however much less than 1.

$$\eta_\nu = \frac{l_\nu}{k_\nu} = \frac{\text{line absorption co-efficient}}{\text{continuous absorption co-efficient}}, \quad (2)$$

is assumed to be independent of the optical depth.

$$a + b = 1, \text{ } a \text{ and } b \text{ are both positive.} \quad \dots \quad (3)$$

The second term on the right hand side of (1) gives the coherent part of emission while the last term in the equation (1) accounts for the non-coherent part of emission. $J(t)$ will be called pseudo average intensity and will be regarded to be insensitive to the variation of frequency over the absorption line considered. The boundary conditions are

$$I_\nu(0, -\mu') = 0, 0 < \mu' \leq 1. \quad \dots \quad (4)$$

$$I_\nu(t, \mu) \exp(-t/\mu\lambda) \rightarrow 0 \text{ as } t \rightarrow \infty, \quad \lambda = 1/(1+\eta_\nu), \quad \dots \quad (5)$$

$$J(t) \rightarrow B_\nu(t) \text{ as } t \rightarrow \infty. \quad \dots \quad (6)$$

where $B_\nu(t)$ is the Planck's function assumed to be constant over the line. We now put

$$\lambda = 1/(1+\eta_\nu), \quad \gamma = 1+c\eta_\nu, \quad \sigma = (1-\epsilon)\eta_\nu, \quad \dots \quad (7)$$

$$U(\mu) = \left\{ \frac{\partial I_\nu(0, \mu)}{\partial \sigma} \right\}_{\sigma \rightarrow 0}, \quad E_n(t) = \int_1^\infty \exp(-xt) dx/x^n, \quad (8)$$

$$D_{r+1}(t) = \frac{t^r}{1 \cdot r!} - \frac{t^{r-1}}{2 \cdot (r-1)!} + \dots + \frac{(-1)^r}{(r+1)!}, \quad (9)$$

$$\phi_{r+1}(t) = D_{r+1}(t) + (-1)^{r+1} E_{r+2}(t), \quad (10)$$

$$\omega' = \sigma \cdot \lambda, \quad \omega = a \cdot \omega', \text{ both } \omega, \omega' \text{ lie between } 0 \text{ and } 1.$$

$$T(z) = 1 - \omega \frac{1}{2} z \ln \frac{z+1}{z-1}, \quad L_1(z) = 1 - \omega' \cdot \lambda \cdot z \ln z + 1/\lambda. \quad (12)$$

$H(z)$ is the unique solution of the integral equation

$$T(z) H(z) = \omega \frac{1}{2} \int_0^1 \frac{x H(x) dx}{x-z} + \sqrt{(1-\omega)}, \quad (13)$$

and

$$H(-z) \rightarrow 1 + (\omega - R_0) \cdot z \cdot \ln z + 0(z) \text{ as } z \rightarrow 0, \quad (14)$$

We further put

$$\omega_0 = \omega'(1+\lambda) - R_0, \quad (15)$$

$$L_2(z) = 1 - \omega_0 z \ln \frac{z+1}{z}, \quad (16)$$

$$U(z) = H(-z)L_1(z) - L_2(z) = u_0 + U_-(z) - U_+(z), \quad (17)$$

where $u_0 = L_1 U(z)$ and $U_-(z)$ is a function regular outside a loop enclosing the branch cut $(0, -1/\lambda)$ on the left of the imaginary axis, while $U_+(z)$ is a function regular outside a loop enclosing the cut $(0, 1)$ and the pole K (real) which is the positive real root of $T(z)$ outside the cut $(0, 1)$.

$$B_\nu(t) = \sum_0^N b_r t^r, \quad g^0(z) = -\frac{1}{2} \sum_0^N b_r r! \lambda^r z^r, \quad \dots \quad (18)$$

$$Q^0(z) = \sum_0^N Q_r^0 z^r, \quad Q_r^0 = \frac{1}{2} \sum_{s=0}^N \frac{b_{r+s}(r+s)!}{s+1} \quad \dots \quad (19)$$

$$R(z) = \sum_0^N \frac{r+1-\epsilon}{1-\epsilon} b_r r! z^r, \quad \dots \quad (20)$$

$$f^0(z) = \sum_0^N \{b\omega'(Q_r^0 + Q_r^0) + \lambda\gamma b_r r!\} \lambda^r z^r, \quad \dots \quad (21)$$

where $C^0(z) = \sum c_r^0 z^r$, c_r^0 's are determined from the boundary condition (6), (22)

$$\delta_0 = \text{wing-damping constant of a broadened line,} \quad (23)$$

$$\delta = \text{damping constant of the profile of the absorption co-efficient,} \quad (24)$$

$$r_0(\mu) = \text{central residual intensity of the line,} \quad (25)$$

$$I_r^c(0, \mu) = \sum_{r=0}^N b_r r! \mu^r = \text{intensity in the continuum,} \quad (26)$$

$$\beta = \frac{\delta_0^2}{(1-\epsilon)\delta^2\eta_r}, \quad G(z) = \frac{1}{2}\omega' \int_0^1 \frac{x I_r(0, x) dx}{x-z} \quad (27)$$

The solution of the integro-differential equation (1) is obtained with the help of Laplace- transformation in combination with the principle of analytic continuation. In obtaining our solution it has been possible to avoid the normal practice of assuming an approximate form of $J(t)$. We have been able to find an explicit, closed expression for $J(t)$ by a new approach based on the expansion of $I_r(0, \mu)$ in powers of σ (justification for this expansion has been advanced).

If $C(z)$ in (8) is assumed to be a polynomial in z (an assumption analytically unjustifiable) we can find an expression depending on the coefficients b_r 's and a_r 's provided $r_0(z)$ can be determined by $r_0(z) = \sum_0^N a_r z^r / I_r^c(0, z)$. The solution of (1) is then obtained on this basis.

However an analytically correct expression for $C(z)$ has been found and is given by

$$C(z) = Q^0(z) + \left\{ \sum_0^N b_r r! z^r \right\} \frac{1}{2} \ln \frac{z+1}{z} - R(z) + b C^0(z), \quad \dots \quad (28)$$

and then the pseudo average intensity $J(t)$ is obtained as

$$J(t) = \sum_0^N Q_r^0 t^r / r! + \sum_0^N C_r^0 t^r / r! + \frac{1}{2} \sum_0^N b_r r! \phi_{r+1}(t). \quad \dots \quad (29)$$

After getting an expression for $J(t)$ as given by (29) it is possible to solve the equation (1) and the emergent intensity is then obtained and given by

$$I_r(0, z) = H(z) A^0(z) + b H(z) g^0(z) \{U_-(z) + L_2(z)\}, \quad \dots \quad (30)$$

where

$$A^0(z) = \text{Lt.}_{z \rightarrow \infty} \{b J^0(z) [u_0 - U_+(z)] + H(-z) [a J(z) + f^0(z) - b g^0(z)]\} \quad \dots \quad (31)$$

From the solution (30) we can get the emergent intensity for coherent scattering simply by putting $b = 0$ in it (as we should). The solution based on the polynomial representation of $C(z)$ is defective in this respect. The solution for completely non-coherent scattering is deduced by putting $a = 0$ in (30). The expression (29) giving $J(t)$ is interesting.

REFERENCE

W. Busbridge, M. N., 1953, **113**, 52.